Fig. 1

TIMER SETTING:	DISPLAY WILL READ:
Always On – Steady Illumination	AO
OFF	OF
Dusk – on for 2 hours	2H
Dusk – on for 4 hours	4H
Dusk – on for 6 hours	6H
Dusk – on for 8 hours	8H
Dusk to Dawn	dd
Outl t Overload	ER

Fig. 3

Fig. 2

| Show Number	Show Description
01	**Steady On**
	Steady On (no effects)
02	**Cascading Flash/Fade On**
	Progressive/3 Flashes and Fade On/ Chase Up
03	**Flash/Fade On**
	Progressive 8 Flashes/Progressive Fade On/Flash Twice/Down to Steady On
04	**Fade Up and Down**
	Progressive Fades On/Steady On/Regressive Fades Off to Total Off
05	**Medium Speed Fade On**
	Progressive Med. Speed Fade On/Cycles Twice/Steady On
06	**Slow Fade On**
	Progressive Slow Fade On /Off/Steady On
07	**Random Flashing and Fading**
	Random Flash/Random Fade On in Random Sequence (ideal for Halloween Decorating)
08	**Variable Chasing**
	Progressive Slow Chase/Speeds Into Fast Chase Up/Regressive Chase/Sequence Chase Up/Sequence Chase Down/Progressive Chase/Regressive Chase
09	**Cascade Chasing**
	Progressive Medium Speed Chase Up - 9 cycles
10	**Cascade Chasing Up and Down**
	Progressive Medium Speed Chase Up/Progressive Medium Speed Chase Down
11	**Fast Chasing**
	Progressive Fast Chase
12	**Cascading Fade On/Fade Off**
	Progressive Fade On To Steady On/Progressive Fade On to Off
13	**3 X 2 Cascading Fade On/Fade Off**
	Outlets 1&2, 3&4, and 5&6 in tandem -Fade On To Steady On/Progressive Fade Off to Off/Cycles
14	**Cascade On/Steady On/Cascade Fade Off**
	Progressive Slow Chase to Steady On/Regressive Slow Chase to Off/2 Cycles
15	**Cascading Fade On/Steady On/Cascade Fade Off**
	Progressive Fade to Steady On/Regressive Fade to Off/1 Cycle
16	**Random Flash**
	Random Sequence of Slow Flash to Fast Flash
17	**3 X 2 Chasing**
	Outlets 1&2, 3&4, and 5&6 Progressively Chase in Tandem
18	**4 Outlets Fade Up & Down (Outlets 5 and 6 Steady On)**
	Outlet 1 thru 4 Progressive Fade On to Steady On in Tandem/Progressive Fade to Off
	Outlets 5&6 are Steady On Function (ideal for using animated lighting or chasing lights – these outlets will not interfere with the functions of lights using their own control boxes or motors)
19	**ALL Programs 01-18 in Sequence**
	All SHOWs play in Sequence – Starting 02 Up to 18 for maximum presentation of effects

Fig. 4

Fig. 5

Fig. 6

Control Device

500

520

Transceiver

Master   Slove

510

Fig. 7